



TECH NOTE
Super Edit™ Version 7.1D and later

JVC BR-D85U

1. **Machine Type** - Machine is Digital-S Component 422.
2. **Pre-Read** - Machine has Pre-Read capability. Control of Pre-Read is from Super Edit [SHIFT][YES] and [SHIFT][NO] or through PEGS.
3. **Program Motion** - Controllable from Super. Accuracy and picture quality is a function of the VTR and varies depending on speed.
4. **Machine Menu Setup** - These are accessed via the MENU key on the VTR's front panel. Most options can be set per user preference. The following are suggested settings of certain options for best performance with Super Edit:

005	Auto Tracking - ON
311	Auto Play - OFF
312	Auto Rew - OFF
317	9 Pin Device ID - JVC D80 (Required)
340	Search Speed - X32
355	PB/EE Select Standby - PB